Inside / IT-palvelut / ... / Tulostusohjeita / Tulostus Macistä

Tulostus Macistä

Tulostimen lisääminen

IT:n ylläpidossa olevissa koneissa on (tulee olla) käyttäjillä oikeudet lisätä tulostimia ilman adminoikeuksia.

Tulostimen voi lisätä joko System Preferences työkalun kautta tai suoraan sovellusohjelmasta.

4	Grah	Filo	Edit	Capture	Win
1	Grab	File	Edit	Capture	win
A So A	bout Thi oftware I op Store	s Mac Jpdate 	·		
Sy	stem Pr	eferen	ces		
D	ock			•	
Re	ecent Ite	ms		►	
Fo	orce Qui	t		CHO	
SI Re St	eep estart nut Dow	n		╲╫ᆃ	
Lo	og Out			企業Q	



Show All	Print & Fax	Q
	No printer Click Add (+) t	rs are available. to set up a printer.
Defaul	fault printer: Last Printer Used t paper size: A4	\$ \$
Click the lock to make change	es.	?
00	Add Printer	\bigcirc
Default Fax IP Windows	Q Search	
Printer Name PRINT01-U9021-psc5 PRINT01-U9021-psc6 PRINT01-U9021-psc7 PRINT01-U9021-psc8 PRINT01-U9021-psc8 PRINT01-U9021-psc401 PRINT01-U9021-s8215 PRINT01-U9021-s8215 PRINT01-U9021-s8215 PRINT01-U9021-tuas117402 PRINT01-U9021-tuas1521 PRINT01-U9021-tuasps1141 PRINT01-U9021-tuasps1141	Kind Open Directory Open Directory	AALTO T21000- T21000- T21000- T21000- T21000- T21000- T21000-
Name: PRINT01-U9021-	-psy347	T21000- T21000- T21000-
Print Using: Choose a Driver	or Printer Model	
Software for this pri printer's manufactu	inter isn't available from Apple. Conta rer for the latest software.	inct the

AALTO DESIGN FACTORY PRINTERS ARE:

T21000-PS1 - BASEMENT T21000-PS2 - COMPANY PLAZA T21000-PS3 - RESEARCH PLAZA T21000-PSC4 - COPY ROOM T21000-PS4 - STAFF WING T21000-PS5 - THE BARN T21000-PS6 - BALCONY

Yleensä tulostusajuriksi voi valita "Print Using" -kohdasta "Generic PostScript Printer".



Ajurin valitsemisen jälkeen Add-nappia painamalla päästään seuraavaan tilanteeseen:

000	Print & Fax	
Show All	Q	\square
Printers PRINT01-U9021-ps o Idle, Last Used	PRINT01-U9021-psy347 Open Print Queue Options & Supplies Location: Otaniemi/Päärakennus/3.krs/Y347 Kind: Generic PostScript Printer Status: Idle Share this printer on the network Sharing Preferences	
+ -		
Defa	t printer: Last Printer Used	
Default p	per size: A4	
Click the lock to make changes	(?)

Mikäli laitteessa on duplexer-toiminto ja halutaan kaksipuoleinen tulostus Generic Postscript-ajurilla, tulee "Options & Supplies" -kohdasta valita Driver-välilehti ja tässä rasti ruutuun kohtaan "Duplex Printing Unit".

Name:	PRINT01-U9021-psy347
Location:	Otaniemi/Päärakennus/3.krs/Y347
Queue Name:	PRINT01_U9021_psy347
Driver Version:	1.0
URL:	smb://PRINT01.org.aalto.fi/U9021-psy347
	(Cancel) (Cancel)
	General Driver Supply Levels
	General Driver Supply Levels
Print Using:	General Driver Supply Levels
Print Using: C Fo take full advant tere. For informati documentation.	General Driver Supply Levels Generic PostScript Printer tage of your printer's options, confirm that they are accurately shown ion on your printer and its optional hardware, check the printer's
Print Using: C To take full advant nere. For informati documentation.	General Driver Supply Levels Generic PostScript Printer tage of your printer's options, confirm that they are accurately shown ion on your printer and its optional hardware, check the printer's
Print Using: C To take full advant here. For informati documentation. Duplex Printing	General Driver Supply Levels Generic PostScript Printer tage of your printer's options, confirm that they are accurately shown ion on your printer and its optional hardware, check the printer's g Unit
Print Using: C To take full advant here. For informati documentation.	General Driver Supply Levels Generic PostScript Printer tage of your printer's options, confirm that they are accurately shown ion on your printer and its optional hardware, check the printer's g Unit
Print Using: C To take full advant here. For informati documentation. Duplex Printing	General Driver Supply Levels Generic PostScript Printer tage of your printer's options, confirm that they are accurately shown ion on your printer and its optional hardware, check the printer's g Unit
Print Using: C To take full advant here. For informati documentation. Duplex Printing	General Driver Supply Levels Generic PostScript Printer tage of your printer's options, confirm that they are accurately shown ion on your printer and its optional hardware, check the printer's g Unit
Print Using: C To take full advant here. For informati documentation.	General Driver Supply Levels Generic PostScript Printer tage of your printer's options, confirm that they are accurately shown ion on your printer and its optional hardware, check the printer's g Unit
Print Using: C To take full advant here. For informati documentation.	General Driver Supply Levels Generic PostScript Printer tage of your printer's options, confirm that they are accurately shown ion on your printer and its optional hardware, check the printer's g Unit

Tulostaminen

Oletetaan, että haluamme tulostaa vaikkapa Safarista sivun. Valitaan Safarin valikosta File ja Print...

🛒 🐔 Safari	File Edit View	History	Bookmarks	6 Window	Help			
	New Window New Tab Open File Open Location		光N 光T 光O 光L					
	Close Window Close Tab Save As		₩W ₩S					
	Mail Contents o Mail Link to Thi Open in Dashbo	f This Page s Page bard	策 企業					
	Import Bookma Export Bookma	rks 'ks						
ļ	Print	k	жР					
		Harris C.	Pa Ori	Printer: P Presets: S Copies: 1 Pages: 0 uper Size: A entation: 1 Sa	All From: 1 4 iii iiiiiiiiiiiiiiiiiiiiiiiiiiiiiii	Collated to: Scale	47 Two-Sided	•
	1 of 2	• •			M Print hea	aders and	footers	
PDF	vttää käyttäjän koko n	imen "Name:'	' -kohtaan. Tä	llä tavoin tulos	taminen ei k	uitenkaan t	Cancel (Print

Nimi on itse korjattava varsinaiseksi käyttäjätunnukseksi.

Enter your name and password for the printer "PRINT01-U9021-psy347". Connect as: O Guest				
Name: tteekkari				
Remember this password in my keychain				
Cancel OK				

Yleisesti Aallon "Windows"-tulostimet vaativat Aalto-salasanan täyttämisen "Password"-kenttään.

	Enter your name and password for the printer "PRINT01-U9021-psy347".				
	Connect as: 🔘 Guest				
	Registered User				
	Name: tteekkari				
	Password:				
Remember this password in my keychain					
	Cancel OK				

1

Oikeat tiedot täyttämällä ja painamalla OK pitäisi tulostuksen onnistua.

Tallennetun salasanan poistaminen Keychainista

Salasanojen tallentamista ei suositella. Mikäli kuitenkin tallensi salasanansa "Remember this password in my keychain" toiminnolla niin viimeistään seuraavan kerran salasanan vaihtuessa tulee ongelmia. Salasana kun ei päivitty avainnippuun itsekseen vaan se pitää itse käydä sieltä päivittämässä. Tämä tapahtuu Keychain Access - työkalun avulla. Keychain Access löytyy /Applications/Utilities alta. Työkalun saa auki mm. klikkaamalla ruudun oikeassa yläkulmassa olevaa suurennuslasikuvaketta (Spotlight) ja kirjoittamalla hakukenttään "Keychain Access".



Keychain Accessin avainnipussa on tulostimen nimellä "Network password" tyyppinen avain jos salasana on tallennettuna. Avaimen saa poistettua klikkaamalla sitä hiiren oikealla näppäimellä, tai yksinäppäimisen hiiren tapauksessa Ctrl + klikkaus, ja valitsemalla valikosta Delete. Tämän jälkeen tulostimen pitäisi kysyä taas salasanaa normaalisti.

000		Keychain Access				
Click to lock the login keychain.				٩		
Keychains login Kicrosoft_Intermediate_Certificates System System Roots	PRINTO J Kind: Net Account: Where: PF Modified:	1–U9021–psy347 work password tteekkari RINT01–U9021–psy347 : Today, 3:34 PM				
	Name		Kind 🔻	Date Modified	Keychain	
	A PRINT01-U9021-p	sy347	Network password	Today, 3:34 PM	login	Copy Passwo
Category	@		HomeSync Password	May 14, 2010 3:44:24 PM	login	Copy rasswo
All Items	\mathbf{A}		application password	Jun 29, 2010 1:56:51 PM	login	Copy "PRINT(
/ Passwords	A		application password	Jun 29, 2010 1:56:52 PM	login	Delete "PRINT
A Passwords	A		application password	May 14, 2010 3:49:25 PM	login	
Secure Notes	A		application password	Aug 16, 2010 10:26:02 AM	login	Get Info
My Certificates	A		application password	Feb 7, 2011 12:57:24 PM	login	
🖗 Keys	A		application password	Nov 18, 2010 12:33:04 PM	login	
📴 Certificates						
	+ i Copy		8 items		11.	

Keskustele artikkelista